PRO-flex ACF 5000_3

Single Phase AC Current Probe

ACF5000_3_081003_07





The new PRO-flex ACF 5000 3 is an AC current probe utilizing the Rogowski principle. It can be used to measure currents up to 5000 A from very low frequencies to 10kHz.

The flexible and lightweight measuring head allows quick and easy installation in hard to reach areas and with large conductors.



Electrical Characteristics

Current Ranges 100A / 1000A / 5000A AC RMS (selectable via rotary switch)

Output Sensitivity 20mV / 2mV / 0.4mV per A (AC coupled)

Accuracy (at 25°C) ± 1% of reading ± 0.1A (100A range)

 \pm 1% of reading \pm 1A (100A / 5000A range)

Load Impedance 100kΩ minimum

± 0.2% of reading (10% to 100% of range) Linearity 80mA (100A) / 400mA (1000A / 5000A range) Noise

Bandwidth 10Hz to 10kHz (-1dB) Phase Error

± <1° (45 - 65Hz)

± 0.1% of reading / °C Temperature Coefficient

Position Sensitivity ± 2% of reading **External Field** ± 0.2% of range

(with cable > 100mm from the head)

Working Voltage 1000V AC RMS or DC (Probe and Integrator) (see Safety Standards section)

30V max (Output)

General Characteristics

Probe and Cable Material Alcryn 2070 NC LATENE 7H2W V0

Probe Cable Length 610mm (24") / 915mm (36") / 1220mm (48")

Probe Cable Diameter 9.9mm (nominal)

Cable Length 2m (Probe to Integrator box) Output

0.5m long lead terminated with

a 6-pin male LEMO

-20 to +65°C **Operating Temperature Range**

Storage Temperature Range -40 to +75°C

Operating Humidity 15% to 85% (non condensing) Degree of protection IP65 Probe, IP40 Integrator module

RAL 120 70 75 Lemon green

AUTHORIZED DISTRIBUTOR



POWERetc Corporation

Colour

Santa Clara, CA 95054 (408) 540-3199

Exclusive GMC-I PROSyS Distributor of Americas

www.poweretc.com info@poweretc.com

PRO-flex ACF 5000_3

Single Phase AC Current Probe

ACF5000_3_081003_07



Safety Standards

EN 61010-1:2001 EN 61010-031:2002 EN 61010-2-032:2002 UL 610101, 2nd Edition, 2005-07-22 CAN/CSA-22.2 No. 61010-1, 2nd Edition, 2004-07

1000 VRMS, Category III, 600 VRMS, Category IV, Pollution Degree 2 (Probe and Integrator)

Limitations Use of the probe on uninsulated conductors

is limited to 1000 V AC RMS or DC and

frequencies below 1 kHz.

Compliance ROHS and WEEE

Compatible Instruments

Fluke Power Monitors Fluke 1750, Fluke (RPM) Power Recorder

Ordering Information

Dout No. Mode

P-01.750.0 ACF 5000_3/24 P-01.750.1 ACF 5000_3/36 P-01.750.2 ACF 5000_3/48



AUTHORIZED DISTRIBUTOR



POWERetc Corporation Santa Clara, CA 95054 (408) 540-3199